

## Digital Measuring Amplifier - DMX

Digital 1- or 2-channel amplifier with 10 V and 0/4...20 mA outputs

24bit  $\Sigma$ - $\Delta$ -AD-Transducer for highest precision

Bluetooth connection or button for quick calibration of the measuring point

OLED display or app display for good readability in the cabinet and on site

Quick and easy setup (app-supported)

Very short cycle time (0.5 ms) for time-critical applications



### DIGITAL MEASURING


The **DMX** amplifier is used where sensors with full-range resistance measuring bridges (e.g. strain gauge force transducers) need to be connected with fast analog signals. The main applications are track strain measurement and linear force measurement technology.

For **quick and easy start-up**, the DMX is operated either directly via the buttons on the device or via a user-friendly app on a mobile device.

During regular operation, the **HAEHNE Viewer** app offers several options for process analysis. For example, force values can be recorded on two channels and exported (CSV).

A **cockpit function** offers additional display options.

### ORDERING EXAMPLE



### OPTIONS

Variant: 1-channel amplifier with 10V and 0/4...20mA output

### SCOPE OF DELIVERY

Amplifier unit in DIN rail mount enclosure

**DMX-1:** 1-channel amplifier with 10V and 0/4...20mA output

**DMX-2:** 2-channel amplifier with 2 x 10V and 2 x 0/4...20mA output

App available for Android and iOS

## Pin assignment



Supply voltage		Sensor A				Sensor B			
1	2	3	4	5	6	7	8	9	10
+24 V	0V	U <sub>1A</sub>	GND	U <sub>A</sub>	GND	U <sub>1B</sub>	GND	U <sub>B</sub>	GND

Sensor A				Sensor B			
11	12	13	14	15	16	17	18
V <sub>4+</sub>	V <sub>4-</sub>	V <sub>1+</sub>	V <sub>1-</sub>	V <sub>4+</sub>	V <sub>4-</sub>	V <sub>1+</sub>	V <sub>1-</sub>

Technical Data		
<b>Strain gauge excitation supply</b>		
	Voltage (V <sub>4</sub> )	5 V
	Current max.	120 mA
<b>Zero adjustment compensation voltage</b> (relative to the voltage inputs)		
		-25...0...+25 mV
<b>Total amplification</b>		
	Adjustment range	500-8000 V/V
	Factory adjustment at 1,5 mV/V	1333,33 V/V
	at 1 mV/V	2000 V/V
	at 0,75 mV/V	2666,66 V/V
<b>Signal output</b>		
	Voltage (U <sub>A</sub> , U <sub>B</sub> )	-10...0...+10 V 0 ... 10 V
	min. load resistance	5 kΩ
	Signal rise time (10...90 %)	0,5 ms ... 16 s
	Current (I <sub>A</sub> , I <sub>B</sub> )	adjustable 4...20 mA 0...20 mA
	max. load resistance	600 Ω
<b>Supply voltage*</b>		
	Voltage	24 V DC, 9-36 V
	Current consumption (Standard)	approx. 90 mA
<b>Enclosure protection</b>		
		IP20
<b>Temperature range</b>		
		0...60° C
<b>Terminal cross- section</b>		
		AWG 22-12
* The auxiliary power must be grounded.		



follow us on  
LinkedIn